Peerless Creations LLC 7 Middlebury Blvd Unit 5 Randolph, NJ 07869 USA +1 973-448-7556

DVR MONITOR CONTROLLER

The DVR Monitor Controller is a portable option for HD inspection and monitoring.

With a built-in DVR, these monitors feature real-time viewing, recording, image capture, loop recording and full playback. An ample 7" screen allows for HD viewing and easy camera control. With a removable micro-SD card this unit can support up to 128gb of memory.

Additional features include, power-save mode, USB connectivity, video output, built-in speaker, AC adapter and battery life up to 6 hours. This unit is compatible with all PC-HD series cameras giving the operator many options for use in multiple applications.

Controller Specifications	PC-HDVR7
Video Resolution	1920x1080; 1280x720; 848x480
Video Storage Format	AVI
Frame Rate	Up to 60 fps
Aspect Ratio	16:9
Compression Format	H.264
Image Resolution	5MP: 3200x1800; 3MP: 2592x1356; 2MP: 2048x1152
Image Format	JPG/JPEG
External SD card	MicroSD card up to 128GB
64GB Recording time	24-64 hours
Phono Output	Analog Video
HDMI Output	Digital Video (1920x1080; 1280x720; 848x480)
Mini USB Output	Digital File Transfer
Operating System	Windows & Mac OS
Port	USB 2.0
Illumination Control	Yes
Language	Multiple
Voltage	DC: 7-24V USB DC: 5V
AC Adapter	DC 12v 2A
Current Consumption	<600mA
Built-in Battery	Li-battery 5Ah
Battery Working Time	≈ 8 hours
Dimensions	118mm x 66mm x 17mm
Weight	160g [.35lbs]
Screen Size	108mm W x 64.8mm H
Screen Brightness	400 cd/m ²
Audio Frequency Range	20Hz-20KHz
Audio Compression Format	AAC

Shown with PC-HD19 Camera

00000

© 2023 Peerless Creations LLC. This document provides technical information for the user. Peerless Creations LLC. reserves the right to modify the information in this document as necessary without notification. Peerless Creations LLC. holds no responsibility for any errors that may appear in this document.

P RLESS® CREATIONSLLC